

Hitachi-HiKOKI UR18DSAL(H4Z) - 18V Digital Radio (Tool Only)



Product Description

Features

- **DIGITAL SIGNAL** - Receiving system allows access to Digital Radio Broadcasting for clearer audio.
- **IPX4 Water Resistance** - Degree of protection against ingress of water
- **AUDIO PLAYBACK & RECHARGE FUNCTION** - Equipped with an AUX input terminal and USB charging jack to charge smartphones or portable music players. The protection storage case docks smartphones or portable music players, while the user listens to music
- **EXTRA FEATURES INCLUDE**
 - Radio Data System (RDS)
 - Digital Clock
 - Alarm
 - Sleep mode

Specifications

- Frequency Band
 - FM: 87.5 to 108MHz
 - AM: 522 to 1,629KHz
- Antenna:
 - FM: Rubber antenna
 - AM: Ferrite bar antenna (built-in)
- Speaker: 90mm (7W) x 2
- Input Terminal: AUX IN (ø 3.5mm)
- Output Terminal: USB Charging Jack (5V 1A)
- Max Available Output: AC: 5W x 2, 14.4V: 6W x 2, 18V: 7W x 2
- Power Supply:
 - Slide Battery: DC 14.4V, 18V
 - Mains power supply (using provided AC adapter)
 - Backup Batteries: DC 3.0V, Two AA Batteries
- Dimensions (LxWxH): 366mm x 303mm x 261mm (with antenna retracted)
- Weight 3.4kg (without battery)
- Standard Accessories: AC Adapter, Two AA Batteries (Back up batteries for saving time and radio station settings only), Recharge Cable Holder