

Dunlite DGWGH7ES-2 - Welder Generator - Honda 13HP 6 kVA 5000/200amp - Petrol



Product Description

- **Power Rating:** 7 kVA
- **Cont. Output Watts:** 6000
- **Engine Model:** Honda GX390
- **Phase:** Single
- **Starting System:** Recoil/Electric
- **Fuel Tank Capacity:** 6.5 L
- **Noise Level @ 7m:** 76 dBA
- **Outlets:** 2 x 15 Amp plugs
- **Welder:** 200 Amps
- **Duty Cycle:** 60 %
- **Operation Hours @ 80% Load:** 2.8 hrs
- **Fuel Type:** Unleaded
- **Diam.:** 810 x 520 x 525 mm (L x W x H)
- **Weight:** 86 kg